2D CMOS Laser Measuring Sensor

ZS-L Series

The smart way to get higher performance and more flexibility for your process.




Features

The scalable platform for more flexibility

- Connect and expand up to 9 controllers
- Connect Multi-calculation controller for advanced calculations like evenness or flatness
- Connect Data storage module for process-data logging
- Connect PC software for easy system set up and signal monitoring
- Sensor head with 2D-CMOS technology with high dynamic sensing range for measuring black rubber, plastic, shiny, glass and mirrow surfaces
- · Advanced application settings
- · Easy reconfiguration and teaching

Measurement Tools:

- Hight measurement
- Step measurement
- Thickness measurement
- Flatness measurement
- Average measurement
- Excentricity
- Warpage/Evenness



ZS-L Series B-25

Ordering Information

Sensors

Sensor Heads

| Optical System | Sensing distance | Beam diameter | Resolution*1 | Model |
|--------------------|------------------|---------------|--------------|----------|
| | 50 ± 5 mm | 900 x 60 μm | 0.8 μm | ZS-LD50 |
| Diffuse reflection | 80 ± 15 mm | 900 x 60 μm | 2 μm | ZS-LD80 |
| | 200 ± 50 mm | 900 x 100 μm | 5 μm | ZS-LD200 |
| Regular reflection | 20 ± 1 mm | 900 x 25 μm | 0.25 μm | ZS-LD20T |
| negular reflection | 40 ± 2.5 mm | 2,000 x 35 μm | 0.4 μm | ZS-LD40T |

This is the peak-to-peak displacement conversion value in the displacement output at the measuring center distance in high-precision mode when the number of samples to average is set to 128 and the measuring mode is set to the high-resolution mode. The standard workpiece is white aluminum ceramics in diffuse reflection mode and glass in the regular reflection mode.

Sensor Controllers

| Shape | Supply Voltage | Control outputs | Model |
|--|----------------|-----------------|----------|
| 7.88885 28888 38888 | 24 VDC | NPN outputs | ZS-LDC11 |
| 390.3967.25 3 3 3 00000 rs-sic | 24 VDC = | PNP outputs | ZS-LDC41 |

Multi Controllers

| Shape | Supply Voltage | Control outputs | Model |
|--|----------------|-----------------|----------|
| 202000 200000 | 24 VDC | NPN outputs | ZS-MDC11 |
| Official participation of the state of the s | | PNP outputs | ZS-MDC41 |

Data Storage Units

| Shape | Supply Voltage | Control outputs | Model |
|--------------------|----------------|-----------------|----------|
| 1 | 24 VDC | NPN outputs | ZS-DSU11 |
| MOAVIET IN 44 STOP | 24 VDC | PNP outputs | ZS-DSU41 |

Accessories (Sold Separately)

Controller Link

| Shape | Model |
|-------|--------|
| 71 | ZS-XCN |

Panel Mount Adapter

| Shape | Model | | |
|-------|---------|---------------------------------------|--|
| | ZS-XPM1 | For 1st Controller | |
| | ZS-XPM2 | For expansion (from 2nd Controller on | |

RS-232C Cable for Connecting to a Personal Computer

| Shape | Model | Qty |
|-------|---------|-----|
| | ZS-XRS2 | 1 |

Extension Cables for Sensor Heads

| Cable length | Model | Qty |
|--------------|--------------|-----|
| 1 m | ZS-XC1A | 1 |
| 4 m | ZS-XC4A | 1 |
| 5 m | ZS-XC5B*1,*2 | 1 |
| 8 m | ZS-XC8A | 1 |
| 10 m | ZS-XC10B*1 | 1 |

^{*1.} Up to two ZS-XC B Cables can be connected (22 m max.).

Logging Software

| Name | Model |
|------------------------------------|----------|
| Smart Monitor Zero Professional | ZS-SW11E |

Memory Card

| Model | Model |
|--------------|--------|
| F160-N64S(S) | 64 MB |
| QM300-N128S | 128 MB |
| F160-N256S | 256 MB |

^{*2.} A Robot Cable (ZS-XC5BR) is also available.

Specifications

Sensor Heads

| Item | Model | ZS-L | D20T | ZS-LD40T | | ZS-L | ZS-LD50 ZS | | _D80 | ZS-L | D200 |
|---|----------------|---|--------------------------------------|--------------------|--------------------|-----------------------------------|--------------------|--------------------|--------------------|--------------------|--------------------|
| Applicable C | ontrollers | ZS-LDC Series | | | | | | | | | |
| Optical system | | Regular reflection | Diffuse reflection | Regular reflection | Diffuse reflection | Diffuse reflection | Regular reflection | Diffuse reflection | Regular reflection | Diffuse reflection | Regular reflection |
| Measuring center distance | | 20 mm | 6.3 mm | 40 mm | 30 mm | 50 mm | 47 mm | 80 mm | 78 mm | 200 mm | 200 mm |
| Measuring ra | ange | ±1 mm | ±1 mm | ±2.5 mm | ±2 mm | ±5 mm | ±4 mm | ±15 mm | ±14 mm | ±50 mm | ±48 mm |
| Light source | | | • | Visible s | emiconducto | r laser (wavele | ength: 650 nm | , 1 mW max., | Class 2) | | |
| Beam diame | ter*1 | 900 x | 25 μm | 2,000 x | 35 μm | 900 x | 60 µm | 900 x | 60 µm | 900 x | 100 µm |
| Linearity*2 | | | | | | ±0.1% F.S. | | | | | ±0.25% F.S. |
| Resolution*3 | | 0.25 | μm | 0.4 | μm | 0.8 | μm | 2 | μm | 5 | μm |
| Temperature characteristic ¹⁴ 0.04% F.S./°C 0.02% F.S. | | F.S./°C | 0.02% F.S./°C 0.01% F.S./°C 0.02% F. | | F.S./°C | | | | | | |
| Sampling cy | cle*5 | | | | | 110 |) µs | | | | |
| la dia ataua | NEAR indicator | | | | | nd nearer than de of the meas | | | | | |
| Indicators | FAR indicator | | | | | nd further than de of the meas | | | | | |
| Operating ar nation | nbient illumi- | Illumination on received light surface: 3,000 lx or less (incandescent light) | | | | | | | | | |
| Ambient tem | perature | Operating: 0 to 50°C, Storage: -15 to 60°C (with no icing or condensation) | | | | | | | | | |
| Ambient hun | nidity | Operating and storage: 35% to 85% (with no condensation) | | | | | | | | | |
| Degree of pr | otection | Cable length 0.5 m: IP66, cable length 2 m: IP67 | | | | | | | | | |
| Materials | | Case: Aluminum die-cast, Front cover: Glass | | | | | | | | | |
| Cable length | | 0.5 m, 2 m | | | | | | | | | |
| Weight | | Approx. 350 g | | | | | | | | | |
| Accessories | | | Laser | abels (1 each | for JIS/EN, 3 | for FDA), Fer | rite cores (2), | Insure Locks | (2), Instruction | Sheet | |

^{1.} Defined as 1/e² (13.5 %) of the center optical intensity at the actual measurement center distance (effective value). The beam diameter is sometimes influenced by the ambient conditions of the workpiece, such as leaked light from the main beam.

Sensor Controllers

ZS-LDC11/LDC41

| Sensor Controllers Model | | | ZS-LDC11 | ZS-LDC41 | | | |
|-------------------------------------|---------------|-------------------|---|--|--|--|--|
| No. of samples to average | | | 1, 2, 4, 8, 16, 32, 64, 128, 256, 512, 1024, 2048, or 4096 | | | | |
| Number of mounted Sensors | | S | 1 per Sensor Controller | | | | |
| | Connection me | ethod | Serial I/O: connector, Other: pre- | wired (standard cable length: 2 m) | | | |
| | Serial I/O | USB 2.0 | 1 port, Full Speed | (12 Mbps), MINI-B | | | |
| | Serial I/O | RS-232C | 1 port, 115,2 | 200 bps max. | | | |
| External | Outputs | Judgement outputs | 3 outputs: HIGH, PASS, and LOW NPN open-collector, 30 VDC, 50 mA max., residual voltage: 1.2 V max. | 3 outputs: HIGH, PASS, and LOW PNP open-collector, 50 mA max., residual voltage: 1.2 V max. | | | |
| interface | Outputs | Linear outputs | Voltage output: -10 to 10 | or current (selected by slide switch on base). V, output impedance: 40 . laximum load resistance: 300 . | | | |
| Inputs Laser OFF, Z reset timing, I | | | ON: Short-circuited with 0V terminal or 1.5 V or less OFF: Open (leakage current: 0.1 mA max.) | ON: Short-circuited to supply voltage or within 1.5 V of supply voltage OFF: Open (leakage current: 0.1 mA max.) | | | |
| Functions | | | Display: Measured value, threshold value, voltage/current, received light amount, and resolution Mode, gain, measurement object, head installation Filter: Smooth, average, and differentiation Outputs: Scaling, various hold values, and zero reset I/O settings: Linear (focus/correction), judgements (hysteresis and timer), non-measurement, and bank (switching and clear) System: Save, initialization, measurement information display, communications settings, key lock, language, and data load | | | | |
| Status indic | cators | | HIGH (orange), PASS (green), LOW (orange), LDON (green), ZERO (orange), and ENABLE (green) | | | | |
| Segment display | | Main display | 8-segment red LED, 6 digits | | | | |
| Sub-display | | Sub-display | 8-segment green LED, 6 digits | | | | |
| LCD | | | 16 digits x 2 rows, Color of characters: green, Resolution per character: 5 x 8 pixel matrix | | | | |
| Setting inn | ıte | Setting keys | Direction keys (UP, DOWN, LEFT, and RIGHT), SET | key, ESC key, MENU key, and function keys (1 to 4) | | | |
| Setting inputs Slide switch | | Slide switch | Threshold switch (2 states: High/Low), mode switch (3 states: FUN, TEACH, and RUN) | | | | |
| Power supp | oly voltage | | 21.6 V to 26.4 VDC (including ripple) | | | | |

ZS-L Series B-27

This is the error in the measured value with respect to an ideal straight line. The standard workpiece is white aluminum ceramics in diffuse reflection mode and glass in the regular reflection mode of the ZS-LD20T/40T/50. Linearity may change according to the workpiece.

This is the peak-to-peak displacement conversion value in the displacement output at the measuring center distance in high-precision mode when the number of samples to average is set to 128 and the measuring mode is set to the high-resolution mode. The standard workpiece is white aluminum ceramics in diffuse reflection mode and glass in the regular reflection mode.

^{14.} This is the value obtained at the measuring center distance when the Sensor and workpiece are fixed by an aluminum jig.

⁵. This value is obtained when the measuring mode is set to the high-speed mode.

| Sensor Controllers | Model | ZS-LDC11 | ZS-LDC41 | |
|---------------------|-------------------------------------|--|-------------------|--|
| Current consumption | | 0.5 A max. (when Sensor Head is connected) | | |
| Ambient temperature | | Operating: 0 to 50°C, Storage: -15 to 60°C (with no icing or condensation) | | |
| Ambient humidity | | Operating and storage: 35% to 85% (with no condensation) | | |
| Materials | | Case: Polycarbonate (PC) | | |
| Weight | | Approx. 280 g (excluding packing materials and accessories) | | |
| Accessories | Ferrite core (1), Instruction Sheet | | Instruction Sheet | |


ZS-MDC11/MDC41 Multi-Controllers

Basic specifications are the same as those for the Sensor Controllers.

The following points, however, are different.

- (1) Sensor Heads cannot be connected.
- (2) A maximum 9 of Controllers can be connected. Control Link Units are required to connect Controllers.
- (3) Processing functions between Controllers: Math functions

Controller Link Unit Connection Using the ZS-XCN




Data Storage Units

| Sensor Controllers Model | | Model | ZS-DSU11 | ZS-DSU41 | |
|---|---------------------------|--------------|--|--|--|
| Number of mounted Sensor Heads | | Heads | Cannot be connected | | |
| Number of connectable Controllers | | rollers | 10 Controllers max. (ZS-MDC: 1 Controller, ZS-LDC: 9 Controllers max.)*1 | | |
| Connectable Controllers | | | ZS-LDC□□, ZS-MDC□□ | | |
| External interface | Connection method | | Serial I/O: connector, Other: pre-wired (standard cable length: 2 m) | | |
| | Serial I/O | USB 2.0 | 1 port, Full Speed (12 Mbps), MINI-B | | |
| | | RS-232C | 1 port, 115,200 bps max. | | |
| | Outputs | | 3 outputs: HIGH, PASS, and LOW NPN open-collector, 30 VDC, 50 mA max., residual voltage: 1.2 V max. | 3 outputs: HIGH, PASS, and LOW PNP open-collector, 50 mA max., residual voltage: 1.2 V max. | |
| | Inputs | | ON: Short-circuited with 0V terminal or 1.5 V or less OFF: Open (leakage current: 0.1 mA max.) | ON: Short-circuited to supply voltage or within 1.5 V of supply voltage OFF: Open (leakage current: 0.1 mA max.) | |
| Data resolution | | | 32 bits | | |
| Functions | Logging trigger functions | | Start and stop triggers can be set separately; external triggers, data triggers (self-triggers), and time triggers | | |
| | Other functions | | External banks, alarm outputs, saved data format customization, and clock | | |
| Status indicators | | | OUT (orange), PWR (green), ACCESS (orange), and ERR (red) | | |
| Segment display | | | 8-segment green LEDs, 6 digits | | |
| LCD | | | 16 digits x 2 rows, Color of characters: green, Resolution per character: 5 x 8 pixel matrix | | |
| Setting inputs Setting keys Slide switch | | Setting keys | Direction keys (UP, DOWN, LEFT, and RIGHT), SET key, ESC key, MENU key, and function keys (1 to 4) | | |
| | | Slide switch | Threshold switch (2 states: High/Low), mode switch (3 states: FUN, TEACH, and RUN) | | |
| Power supply voltage | | | 21.6 V to 26.4 VDC (including ripple) | | |
| Current consumption | | | 0.5 A max. | | |
| Ambient temperature | | | Operating: 0 to 50°C, Storage: -15 to 60°C (with no icing or condensation) | | |
| Ambient humidity | | | Operating and storage: 35% to 85% (with no condensation) | | |
| Materials | | <u> </u> | Case: Polycarbonate (PC) | | |
| Weight | | | Approx. 280 g (excluding packing materials and accessories) | | |
| Accessories | | | Ferrite core (1) Instruction Sheet, Tools for Data Storage Unit: CSV File Converter for Data Storage Unit, Smart Analyzer Macro Edition (Excel macros for analysis of collected data) | | |

Control Link Units are required to connect Controllers.


Dimensions Sensor Heads

ZS-LD50/LD80/LD200




Sensor Controllers


ZS-LDC11/LDC41



ZS-LD20T/LD40T





ZS-MDC11/MDC41 Multi-Controllers



Panel Mount Adapters

ZS-XPM1/XPM2 (Dimension for Panel Mounting)






Panel cutout dimensions

(60 X n) + 8

Note 1: Dimensions are shown for a panel thickness of 2.0 mm. n: Number of gang-mounted Controllers (1 to 11)

Data Storage Unit

ZS-DSU11/DSU41



ZS-L Series B-29

Laser Label Indications

Attach the following warning label to the side of the ZS-L-series Sensor Head.



READ AND UNDERSTAND THIS DOCUMENT

Please read and understand this document before using the products. Please consult your OMRON representative if you have any questions or comments.

WARRANTY

OMRON's exclusive warranty is that the products are free from defects in materials and workmanship for a period of one year (or other period if specified) from date of sale by OMRON.

OMRON MAKES NO WARRANTY OR REPRESENTATION, EXPRESS OR IMPLIED, REGARDING NONINFRINGEMENT, MERCHANTABILITY, OR FITNESS FOR PARTICULAR PURPOSE OF THE PRODUCTS. ANY BUYER OR USER ACKNOWLEDGES THAT THE BUYER OR USER ALONE HAS DETERMINED THAT THE PRODUCTS WILL SUITABLY MEET THE REQUIREMENTS OF THEIR INTENDED USE. OMRON DISCLAIMS ALL OTHER WARRANTIES, EXPRESS OR IMPLIED.

LIMITATIONS OF LIABILITY

OMRON SHALL NOT BE RESPONSIBLE FOR SPECIAL, INDI-RECT, OR CONSEQUENTIAL DAMAGES, LOSS OF PROFITS OR COMMERCIAL LOSS IN ANY WAY CONNECTED WITH THE PRODUCTS, WHETHER SUCH CLAIM IS BASED ON CONTRACT, WARRANTY, NEGLIGENCE, OR STRICT LIABILITY.

In no event shall responsibility of OMRON for any act exceed the individual price of the product on which liability is asserted.

IN NO EVENT SHALL OMRON BE RESPONSIBLE FOR WARRANTY, REPAIR, OR OTHER CLAIMS REGARDING THE PRODUCTS UNLESS OMRON'S ANALYSIS CONFIRMS THAT THE PRODUCTS WERE PROPERLY HANDLED, STORED, INSTALLED, AND MAINTAINED AND NOT SUBJECT TO CONTAMINATION, ABUSE, MISUSE, OR INAPPROPRIATE MODIFICATION OR REPAIR.

SUITABILITY FOR USE

THE PRODUCTS CONTAINED IN THIS DOCUMENT ARE NOT SAFETY RATED. THEY ARE NOT DESIGNED OR RATED FOR ENSURING SAFETY OF PERSONS, AND SHOULD NOT BE RELIED UPON AS A SAFETY COMPONENT OR PROTECTIVE DEVICE FOR SUCH PURPOSES. Please refer to separate catalogs for OMRON's safety rated products.

OMRON shall not be responsible for conformity with any standards, codes, or regulations that apply to the combination of products in the customer's application or use of the product.

At the customer's request, OMRON will provide applicable third party certification documents identifying ratings and limitations of use that apply to the products. This information by itself is not sufficient for a complete determination of the suitability of the products in combination with the end product, machine, system, or other application or use.

The following are some examples of applications for which particular attention must be given. This is not intended to be an exhaustive list of all possible uses of the products, nor is it intended to imply that the uses listed may be suitable for the products:

 Outdoor use, uses involving potential chemical contamination or electrical interference, or conditions or uses not described in this document.

- Nuclear energy control systems, combustion systems, railroad systems, aviation systems, medical equipment, amusement machines, vehicles, safety equipment, and installations subject to separate industry or government regulations.
- Systems, machines, and equipment that could present a risk to life or property.

Please know and observe all prohibitions of use applicable to the products.

NEVER USE THE PRODUCTS FOR AN APPLICATION INVOLVING SERIOUS RISK TO LIFE OR PROPERTY WITHOUT ENSURING THAT THE SYSTEM AS A WHOLE HAS BEEN DESIGNED TO ADDRESS THE RISKS, AND THAT THE OMRON PRODUCT IS PROPERLY RATED AND INSTALLED FOR THE INTENDED USE WITHIN THE OVERALL EQUIPMENT OR SYSTEM.

PERFORMANCE DATA

Performance data given in this document is provided as a guide for the user in determining suitability and does not constitute a warranty. It may represent the result of OMRON's test conditions, and the users must correlate it to actual application requirements. Actual performance is subject to the OMRON Warranty and Limitations of Liability.

CHANGE IN SPECIFICATIONS

Product specifications and accessories may be changed at any time based on improvements and other reasons.

It is our practice to change model numbers when published ratings or features are changed, or when significant construction changes are made. However, some specifications of the product may be changed without any notice. When in doubt, special model numbers may be assigned to fix or establish key specifications for your application on your request. Please consult with your OMRON representative at any time to confirm actual specifications of purchased products.

DIMENSIONS AND WEIGHTS

Dimensions and weights are nominal and are not to be used for manufacturing purposes, even when tolerances are shown.

ERRORS AND OMISSIONS

The information in this document has been carefully checked and is believed to be accurate; however, no responsibility is assumed for clerical, typographical, or proofreading errors, or omissions.

PROGRAMMABLE PRODUCTS

OMRON shall not be responsible for the user's programming of a programmable product, or any consequence thereof.

COPYRIGHT AND COPY PERMISSION

This document shall not be copied for sales or promotions without permission.

This document is protected by copyright and is intended solely for use in conjunction with the product. Please notify us before copying or reproducing this document in any manner, for any other purpose. If copying or transmitting this document to another, please copy or transmit it in its entirety.

ALL DIMENSIONS SHOWN ARE IN MILLIMETERS.

To convert millimeters into inches, multiply by 0.03937. To convert grams into ounces, multiply by 0.03527.

Cat. No. Z215-E2-01A-X

In the interest of product improvement, specifications are subject to change without notice.